



A6D/A6DR

**Auto Sensing
DC/AC 600A
Clamp Meter**

Faster, Smarter and Innovative

- Extra large LCD with 10000 count display.
- Innovative Auto Sensing and Selection Technology facilitate your daily work with better efficiency.
- Much safer Data Hold design preventing from inappropriate operation and avoiding the misleading accidents.
- Faster Auto Hold feature capture every current variation accurately and reliably with audible beeper.
- Automatic sensing backlit extend extra battery life.
- Ergonomically designed over molding with anti-slide grip and better drop proof.

Features

- 10000 Count digital display with auto backlit
- Auto Selection on ACV, DCV, ACA, DCA, Ω , Continuity and Diode Test.
- True RMS reading on AC mode (A6DR).
- Single key operation for all functions.
- Auto Zeroing key for DCA.
- Smart Data Hold.
- Auto Hold (Current mode only).
- AC/DC 600 Amps capability.
- AC 750 Volts/DC 1000 Volts capability
- 10K Ohms Resistance range.
- Faster continuity Beeper.
- Battery capacity auto indication.
- Auto Power Off (Disable).
- Up to 35mm dia. (750MCM) Conductor Size.

Specification

ACV Measurement Range:
(1.3V - 750.0V)

DCV Measurement Range:
(2.1V - 1000V / 0.7V - 1000V)

Resistance Measurement Range:
(0.0 Ω - 9999 Ω)

Diode Measurement Range:
(0.4V - 0.8V)

ACA/DCA Measurement Range:
(0.9A - 600.0A)

